



Optional
AC51928

Description

The 40W battery is listed for field and factory installation. It provides constant power output to the load during emergency mode operation. The battery maintains illumination in the emergency mode for a minimum of 90 minutes. It is an ideal emergency solution for round LED highbay lights.

Remote required for testing (1 per project minimum).

Construction

The 40W battery has an integrated junction box for all fixture connections. Six threaded knockouts provide adequate flexibility of wiring options.

Electrical

The power supply has a range of 120-277V, 50/60Hz. The battery will ONLY operate on fixtures with 0-10V / 1-10V dimming capabilities. See user manual for troubleshooting instructions.

Mounting

The battery back comes standard with an I-bolt on the top and bottom.

Warranty

For warranty information refer to: www.venturelighting.com/resources/warranties

Product Performance

Wattage	40W
Lumen Output	Fixture Dependent
Operating Temperature Range	0°C – 50°C

Physical Characteristics

Color	Orange
Weight	7.4 lbs (3.4 kg)
Diameter	5.11" (130mm)
Height	9.84" (250mm)

Electrical Characteristics

Input Voltage Range	120-277V
Maximum Fixture Wattage	≤ 300W
Battery Discharge Time	≥ 90 Mins
Battery Type	Li-ion
Fixture Compatibility	0-10V / 1-10V Dimming Required

Regulatory Qualifications

cULus Listed

IP65 Rated for dry, damp, wet locations


Accessories

AC51928 Wireless Test Remote


Venture Round Highbay Battery

Wiring


With Wall Switch





With 0-10V Dimming Wall Switch



With 0-10V Dimming Wall Switch



Dimensions



(800) 451-2606

6675 Parkland Blvd., Suite 100

Solon, Ohio 44139 USA

Email: Venture_Lighting@VentureLighting.com

VentureLighting.com

