



Description

Venture Lighting's LED Retrofit lamps are the ideal upgrade solution to traditional HID lamp technologies. Venture's LED Retrofit lamps are a simple energy saving solution for providing significant maintenance savings. The integrated driver design is an ideal upgrade from traditional technologies.

Features & Benefits

- Energy saving replacement for MH or HPS
- Up to 5 times longer life and 80% energy savings compared to HID
- 5 year warranty
- Universal burn position
- Easy installation
- Reduced maintenance costs
- **Note: It is the customer's responsibility to verify that the lamp compartment meets the minimum required lamp compartment dimension of 5.79" diameter by 16" long.*

Applications

- Post top
- Wall pack
- Area Lighting
- Flood lighting
- Garage lighting
- General illumination

Notes

- The use of an external surge protection device is recommended
- Operating temp. range between -22°F and 113°F (-30°C and 45°C)
- Suitable for use in dry and damp environments
- Suitable for use in portable, surface mounted and ceiling luminaires
- Suitable for use in totally enclosed, recessed luminaires.
- Do not use where exposed to water or outdoors without an appropriate enclosed luminaire.
- Lamps have clear polycarbonate cover lenses

OR100-50BE39

Product Performance

Input Power (W)	100
Bare Lamp Lumens	13500
DLC Rated Lumens	11460
Lumens/Watt (Bare Lamp)	114
Correlated Color Temperature (CCT)	5000K
Color Rendering Index (CRI)	80
Life Hours	50000
Minimum Lamp Compartment Size	5.8" Dia by 16" long
Dimming	No
Operating Temperature Range	-22°F to 113°F (-30°C to 45°C)

Physical Characteristics

Base Type	Mogul (E39)
Overall Length A	11.42" (290mm)
Diameter B	4.91" (125mm)
Weight	2.6 lbs (1180 g)

Electrical Characteristics

Input Voltage Range	120V-277V; 50/60Hz
Driver	Internal within lamp
Power Factor	>0.90
THD	<20%

Regulatory Qualifications

cULus Listed

cULus Classified – Certified to UL 1598C



DLC® Premium Qualified - Model# OR100-50BE39

Accessories

SP12714 – 120-277V Surge Protector



Venture 100W LED Retrofit Lamp



Easy to install - bypass ballast and provide voltage directly to lamp

(800) 451-2606
Fax: (800) 451-2605
7905 Cochran Rd, Suite 300
Glenwillow, Ohio 44139
E-mail: Venture_Lighting@VentureLighting.com
VentureLighting.com

