

45W LED Retrofit Lamp

Order Code: LP26126



Description

Venture Lighting's LED Retrofit lamps are the ideal upgrade solution to traditional HID lamp technologies. Venture's LED Retrofit lamps are a simple energy saving solution for providing significant maintenance savings. The integrated driver design is an ideal upgrade from traditional technologies.

Feature & Benefits

- Energy savings replacement for MH or HPS
- Up to 5 times longer life and 80% energy savings compared to HID
- 5 year warranty
- Universal burn position
- Easy installation
- Reduced maintenance costs

Applications

- Post top
- Wallpack
- Area lighting
- Flood lighting
- Garage lighting
- General illumination

Notes

- The use of an external surge protection device is recommended
- Operating temp. range between -40°F and 122°F (-40°C and 50°C)
- Suitable for use in dry and damp environments
- Suitable for use in portable, surface mounted and ceiling luminaires
- Suitable for use in open and enclosed luminaires
- Do not use where exposed to water or outdoors without an appropriate enclosed luminaire
- Lamps have clear polycarbonate cover lenses

Warranty

For warranty information refer to: www.venturelighting.com/resources/warranties


Product Performance	
Input Power (W)	45
Bare Lamp Lumens	5400
DLC Rated Lumens	4200
Lumens/Watt (Bare Lamp)	120
Correlated Color Temperature (CCT)	5000K
Color Rendering Index (CRI)	80
Life Hours	50000
Min. Lamp Compartment (H x L x W)	11" x 8" x 8" (279mm x 203mm x 203mm)
Dimming	No
Operating Temperature Range	-40°F to 122°F (-40°C to 50°C)
Physical Characteristics	
Base Type	Mogul (E39)
Overall Length A	10.13" (257mm)
Diameter B	3.66" (93mm)
Weight	2.06 lbs (933 g)
Electrical Characteristics	
Input Voltage Range	100-277V; 50/60Hz
Driver	Internal within lamp
Power Factor	≥ 90%
THD	<u>≤</u> 20%
Regulatory Qualifications	
cULus Listed (UL 1993/CSA C22.2 No. 1993)	
cULus Classified (UL 1598C/CSA C22.2 No. 250.1)	
Accessories	
SP12714 120-277V Surge Protector	


Revision: 06, 07-Sept 2022





Venture 45W LED Retrofit Lamp





Easy to install - bypass ballast and provide voltage directly to lamp

(800) 451-2606

6675 Parkland Blvd., Suite 100 Solon, Ohio 44139 USA

 ${\it Email}. \ {\it Venture_Lighting@VentureLighting.com}$

VentureLighting.com

