

36W LED Retrofit Lamp

Order Code: LP51734



Description

Venture Lighting's LED Retrofit lamps are the ideal upgrade solution to traditional HID lamp technologies. Venture's LED Retrofit lamps are a simple energy saving solution for providing significant maintenance savings. The integrated driver design is an ideal upgrade from traditional technologies.

Feature & Benefits

- Replaces MH or HPS up to 175W
- · Replaces CFL up to 85W
- 5 year warranty
- Universal burn position
- Easy installation
- Reduced maintenance costs

Applications

- Post top
- Wallpack
- Area lighting
- Flood lighting
- Garage lighting
- General illumination

Notes

- The use of an external surge protection device is recommended
- Operating temp. range between -40°F and 122°F (-40°C and 50°C)
- Suitable for use in dry and damp environments
- Suitable for use in portable, surface mounted and ceiling luminaires
- Suitable for use in open and enclosed luminaires
- Do not use where exposed to water or outdoors without an appropriate enclosed luminaire
- Lamps have clear polycarbonate cover lenses

Warranty

For warranty information refer to: www.venturelighting.com/resources/warranties


Product Performance	
Input Power (W)	36
Initial Lumens	5000
Lumens/Watt	135
Correlated Color Temperature (CCT)	4000K
Color Rendering Index (CRI)	80
Life Hours	50000
Min. Lamp Compartment (H x L x W)	17.4" x 9.3" x 9.3" (442mm x 236mm x 236mm)
Dimming	No
Operating Temperature Range	-40°F to 122°F (-40°C to 50°C)
Physical Characteristics	
Base Type	Medium (E26)
Overall Length A	10.16" (258mm)
Diameter B	3.66" (93mm)
Weight	1.8 lbs (816 g)
Electrical Characteristics	
Input Voltage Range	100-277V; 50/60Hz
Driver	Internal within lamp
Power Factor	≥ 90%
THD	<u>≤</u> 20%
Regulatory Qualifications	
cULus Listed (UL 1993/CSA C22.2 No. 1993	3)
cULus Classified (UL 1598C/CSA C22.2 No.	250.1)
Accessories	
SP12714 120-277V Surge Protector	


Revision: 04, 07-Sept 2022





Venture 36W LED Retrofit Lamp





Easy to install - bypass ballast and provide voltage directly to lamp

(800) 451-2606

6675 Parkland Blvd., Suite 100 Solon, Ohio 44139 USA

 ${\it Email}. \ {\it Venture_Lighting@VentureLighting.com}$

VentureLighting.com

